



VHF AND UHF TRANSCEIVERS

IC-F51 ATEX (VHF Transceiver)

IC-F61 ATEX (UHF Transceiver)



INTRINSICALLY SAFE VERSION



BIS 1200
Compatible

IP67

Rugged
MIL-STD 810

Photo includes optional speaker-microphone, HM-138.

Superior Water Supports De

Firefighters, Police, Security, and many other professions face unique challenges, but all have one thing in common: they need reliable communication. Icom's IC-F51/F61 offers a complete solution. Rain or shine, this radio keeps you connected.

Dust and Waterproof Protection Equivalent to IP67

The gasket sealed waterproof housing provides superior dust and waterproof protection, equivalent to IP67.

Reliable and dependable use in harsh conditions under water or dust, make the IC-F51 / IC-F61 the radio for all situations.

* 1m depth of water for 30 minutes.



Built-in Tone Signaling

Use the built-in CTCSS, DTCS, 2-Tone and 5-Tone capability to set up your own talk groups and quiet stand-by when other groups are talking. You can also set up selective calls to individuals or control a repeater.

Multiple 5-Tone

Up to 8 5-Tone codes can be decoded on a single memory channel. This is perfect for professionals who require multiple district paging on one channel. When a matched tone is received, the following items are programmable for each code.

- Bell icon
- Answer back
- Stun
- Beep sound
- Auto transmit
- Scan
- ID decode
- Emergency cancel

VHF AND UHF TRANSCIVERS

IC-F51 ATEX
VHF Transceiver

IC-F61 ATEX
UHF Transceiver



▼ IC-F51 ATEX

▼ IC-F61 ATEX



Waterproof Protection Demanding Communication

and Public utilities. Each profession has its own unique thing in common: the need for reliable communications. Compact waterproof, MIL STD package, that's easy to use. Keeps you in contact in nearly any environment.



Up to 7 Programmable Buttons

The [P0]–[P3], [Red] and [Up], [Down] buttons are programmable to meet specific needs. The [Red] button on the top panel can be assigned as an emergency trigger.

Alphanumeric Display

The 8-character alphanumeric display shows channel, bank, tone code and scanning channel names on the display. 7 operational icons on the sub-line show various status at a glance.



Upper and lower case characters available.

Built-in Voice Scrambler

The IC-F51/F61 has a built-in rolling type voice scrambler equivalent to the UT-110.

Wide Range Coverage and Large Channel Capacity

The IC-F51 covers 136–174MHz and the IC-F61 covers 400–470MHz in one version. The 128 memory channels with 8 memory banks allows you to divide and store a variety of channels from local to wide area network channels. Wide, middle and narrow* channel bandwidth is programmable to each channel.

(* Programmable 25/12.5kHz or 20/12.5kHz Ch.)

Li-Ion Battery Pack

The large capacity 1950mAh (typ.) Lithium-Ion (Li-Ion) battery pack, BP-227AXD provides a practical 10 hours* of operating time. Li-Ion batteries allow flexible charging and have almost no memory effect.

* Typical operation Tx:Rx:Stand-by=5:5:90

Compact Body

56(W)×97(H)×36.4(D) mm compact body with durable, dependable construction, has been tested to MIL standard specifications. The compact design fits comfortably in your palm, and is easy to carry around.

BIIS 1200 Compatible

The following selective calling and data features are available with the BIIS system.

- 32 abbreviated call memories
- 7 group IDs
- 24-status Messages
- 8-character SDM (Short Data Message)

Other Features

- Built-in audio compander
- 8 DTMF autodial memories
- Normal and priority scans
- 2 step power saver
- Busy, repeater lockout functions
- Power ON password, and more...

ATEX Intrinsically Safe



The IC-F51/F61 and designated options are certified to the ATEX Protection Class II 2 GD Ex ib IIA T3 Ex tD A21 T160°C IP67 as interpreted in the following table. It is suitable for use in hazardous areas where flammable gasses, liquids or combustible dusts are used.

ATEX Gas Protection

II	2	G	D	Ex	ib	IIA	T3	T3 = Device surface temperature will not exceed 200°C
								IIA = Protection in GAS group
								ib = Intrinsically safety according to EN60079-0
								Ex = Explosion proof equipment
								D = Dusts
								G = Gas, vapour and mist
								2 = High level protection for use in zone 1 (gas) and zone 21 (dust)
								II = Group II, other (non-mining) environments

ATEX Gas Group Classification

	T1: 450°C	T2: 300°C	T3: 200°C
I	Methane		
IIA	Acetone	Ethyl alcohol	Benzene
	Ethane	I-amyl acetate	Diesel fuel
	Ethyl acetate	n-butane	Aircraft fuel
	Ammonia	n-butyl alcohol	Heating oil
	Benzene (pure)		n-hexane
	Acetic acid		
	Carbon Monoxide		
	Methanol		
Propane			
Toluene			

ATEX Dust Protection

Ex	tD	A21	T160°C	IP67	IP67 = IP67 dust and water proof protection
					T160°C = Maximum temperature of device surface
					A21 = For use in dust zone 21 environments
					tD = Enclosure protection
					Ex = Explosion proof equipment

SPECIFICATIONS

	IC-F51 ATEX	IC-F61 ATEX IC-F61-L ATEX
GENERAL		
Frequency coverage	136–174MHz	400–470MHz 350–400MHz (Non-RTTE)
Number of channels	Max. 128 channels/ 8 zones	
Type of emission	16K0F3E, 14K0F3E, 8K50F3E	
Channel spacing	12.5/20/25kHz	12.5/20/25kHz
PLL channel step	2.5/3.125kHz	12.5/25kHz (IC-F61-L) 5/6.25kHz
Power supply requirement	7.2V DC nominal	
Current drain (approx.)		
Tx High (at 1W)	0.7A	0.8A
Rx Max. audio Standby	300mA 85mA	300mA 85mA
Antenna impedance	50Ω (SMA type)	
Operating temperature range	–20°C to +55°C	
Dimensions (W×H×D) (Projections not included)	56×97×36.4mm (With BP-227AXD)	
Weight (approx.)	290g (With BP-227AXD)	
TRANSMITTER		
Output power (at 7.2V DC)	1W	
Max. frequency deviation	±5.0kHz/±4.0kHz/±2.5kHz (W/M/N)	
Frequency stability	±2.5ppm	
Spurious emissions	0.25μV (<1GHz) 1.0μV (>1GHz)	
Modulation limiting	60–100% of Max. deviation	
Audio harmonic distortion	3% typ. (AF 1kHz 40% deviation)	
Ext. microphone connector	9-pin multi connector/2.2kΩ	
RECEIVER		
Sensitivity (at 20dB SINAD)	–4dBμV typ. (emf)	
Adjacent channel selectivity	75/73/65dB min. (W/M/N)	
Spurious response	70dB	
Intermodulation rejection	67dB typ.	
Hum and noise	55/53/50dB typ. (W/M/N)	
Audio output power	500mW typ. (at 5% distortion with 8Ω load)	
Ext. speaker connector	9-pin multi connector/8Ω	

Measurements made in accordance with EN 300-086.
All stated specifications are subject to change without notice or obligation.

Applicable U.S. Military Specifications & IP Rating

Standard	MIL 810 F	
	Method	Procedure
Low Pressure	500.4	I, II
High Temperature	501.4	I, II
Low Temperature	502.4	I, II
Temperature Shock	503.4	I
Solar Radiation	505.4	I
Rain Blowing/Drip	506.4	I, III
Humidity	507.4	–
Salt Fog	509.4	–
Dust Blowing	510.4	I
Vibration	514.5	I
Shock	516.5	I, IV

Also meets equivalent MIL-STD-810-C, -D and -E.

Ingress Protection Standard	
Dust & Water	IP67 (Dust-protection and waterproof protection)

ATEX INTRINSICALLY SAFE TYPE APPROVAL

The approved rating is
 Gas: II2GD Ex ib IIA T3
 Dust: II2GD Ex tD A21 T160°C IP67
 Special conditions for use: Must be used with **BP-227AXD**
 When the transceiver is used in hazardous areas, either the jack cover or HM-138 must be attached to the connector.

* Note for IC-F51/F61 ATEX Non-Dust (II2G) version users, please use only the **BP-227AX** battery pack with the IC-F51/F61 ATEX Non-Dust version.

OPTIONS

Some options may not be available in some countries. Please ask your dealer for details.

<p>BATTERY PACK</p>  <p>BP-227AXD Li-Ion 7.4V 1850mAh (min.) 1950mAh (typ.)</p>	<p>BATTERY CHARGER^{*2}</p>  <p>BC-147S^{*1} BC-152 Charges the BP-227AXD in 9–10 hours. (approx.)</p>	<p>RAPID CHARGER^{*2}</p>  <p>BC-145S^{*1} BC-119N+AD-100 Rapidly charges the BP-227AXD in 2–3 hours. (approx.)</p>
<p>MULTI-CHARGER^{*2}</p>  <p>BC-121N+AD-100 (6 pcs.) Rapid charges up to 6 battery packs in 2–2.5 hours.</p>	<p>MULTI-CHARGER^{*2}</p>  <p>BC-157</p>	<p>SPEAKER-MICROPHONE HM-138</p>  <p>IPX7</p>

*1 BC-145SA/BC-147SA for 120V AC. SE for 230V AC. SV for 240V AC. BC-145SUK for 230V AC.
 *2 These chargers are not approved as intrinsically safe. Do not charge the BP-227AXD in an explosive atmosphere.

<p>BELT CLIPS</p>  <p>MB-98 Alligator type MB-86 Swivel type</p>	<p>LEATHER BELT HANGER MB-96F</p> 	<p>ANTENNAS FA-S24V: 136–150MHz (Blue) FA-S59V: 150–174MHz (Red) FA-S27U: 400–470MHz (Green)</p> <p>STUBBY ANTENNAS FA-S62VS: 150–162MHz (Red) FA-S63VS: 160–174MHz (Green) FA-S57US: 450–490MHz (Red)</p>
--	--	--

Supplied accessories: (May differ according to version)

- Antenna (Length may differ according to version)



- Alligator-type belt clip, MB-98
- Battery pack, BP-227AXD

Icom Inc.

1-1-32, Kami-minami, Hirano-ku, Osaka 547-0003, Japan Phone: +81 (06) 6793 5302 Fax: +81 (06) 6793 0013

www.icom.co.jp/world

Count on us!

Icom America Inc.

2380 116th Avenue NE,
Bellevue, WA 98004, U.S.A.
Phone: +1 (425) 454-8155
Fax: +1 (425) 454-1509
E-mail: sales@icomamerica.com
URL: <http://www.icomamerica.com>

Icom New Zealand

146A Harris Road, East Tamaki,
Auckland, New Zealand
Phone: +64 (09) 274 4062
Fax: +64 (09) 274 4708
E-mail: inquiries@icom.co.nz
URL: <http://www.icom.co.nz>

Icom (UK) Ltd.

Blacksale House, Altira Park,
Herne Bay, Kent, CT6 6GZ, U.K.
Phone: +44 (0)1227 741741
Fax: +44 (0)1227 741742
E-mail: info@icomuk.co.uk
URL: <http://www.icomuk.co.uk>

Asia Icom Inc.

6F No. 68, Sec. 1 Cheng-Teh Road,
Taipei, Taiwan, R.O.C.
Phone: +886 (02) 2559 1899
Fax: +886 (02) 2559 1874
E-mail: sales@asia-icom.com
URL: <http://www.asia-icom.com>

Your local distributor/dealer:

Icom Canada

Greenwood Centre #150-6165 Highway 17,
Delta, B.C., V4K 5B8, Canada
Phone: +1 (604) 952-4266
Fax: +1 (604) 952-0090
E-mail: info@icomcanada.com
URL: <http://www.icomcanada.com>

Icom (Europe) GmbH

Communication Equipment
Auf der Krautweide 24
65812 Bad Soden am Taunus, Germany
Phone: +49 (6196) 76685-0
Fax: +49 (6196) 76685-50
E-mail: info@icom-europe.com
URL: <http://www.icomeurope.com>

Icom France s.a.s.

Zac de la Plaine,
1 Rue Brindjonec des Moulains, BP 45804,
31505 Toulouse Cedex 5, France
Phone: +33 (5) 61 36 03 03
Fax: +33 (5) 61 36 03 00
E-mail: icom@icom-france.com
URL: <http://www.icom-france.com>

Beijing Icom Ltd.

10C07 Long Silver Mansion, No.88,
Yong Ding Road, Haidian District,
Beijing, 100039, China
Phone: +86 (010) 5889 5391/5392/5393
Fax: +86 (010) 5889 5395
E-mail: bjicom@bjicom.com
URL: <http://www.bjicom.com>

Icom (Australia) Pty. Ltd.

Unit 1 / 103 Garden Road,
Clayton, VIC 3168 Australia
Phone: +61 (03) 9549 7500
Fax: +61 (03) 9549 7505
E-mail: sales@icom.net.au
URL: <http://www.icom.net.au>

Icom Spain S.L.

Ctra. Rubi, No. 88 "Edificio Can Castanyer"
Baños A 08174, Sant Cugat del Valles,
Barcelona, Spain
Phone: +34 (93) 590 26 70
Fax: +34 (93) 589 04 46
E-mail: icom@icomspain.com
URL: <http://www.icomspain.com>

Icom Polska

81-850 Sopot, ul. 3 Maja 54, Poland
Phone: +48 (58) 550 7135
Fax: +48 (58) 551 0484
E-mail: icompolksa@icompolksa.com.pl
URL: <http://www.icompolksa.com.pl>